




# DIGITAL MULTIMETER

## KM-9696 SERIES



DISPLAY		Red high efficiency LED high 9.14mm (.36")
ACCURACY		$\pm 0.5\% \pm 2$ digit
OPERATING CONDITION		-10°C~50°C (20% to 90% RH non-condensed)
DIELECTRIC STRENGTH		AC 2KV/1min
AUX. POWER		AC110V/220V 50/60Hz
MEASUREMENT RANGE	KM96-3A	<p><b>Display:</b> 3 Windows.  <b>Function:</b> Display 3 Phase Current Simultaneously.  <b>Ranges:</b>            Direct Measurement Current: AC 0 – 5A..            For Current above 5A, Current Transformer (C.T.) must be used.            Press Key "C" to select desirable C. T. Ratio.            The following are the available C.T. Ratios:            10A/5A, 15A/5A, 20A/5A, 25A/5A, 30A/5A, 40A/5A, 50A/5A,60A/5A, 70A/5A, 75A/5A, 80A/5A, 100A/5A, 120A/5A, 150A/5A, 160A/5A,200A/5A, 250A/5A, 300A/5A, 400A/5A, 500A/5A, 600A/5A, 700A/5A, 750A/5A, 800A/5A, 1kA/5A, 1.2kA/5A,1.5kA/5A, 1.6kA/5A, 2kA/5A, 2.5kA/5A, 3kA/5A, 4kA/5A, 5kA/5A,6kA/5A, 7kA/5A,7.5kA/5A, 8kA/5A.            Note: Red LED indicates Ampere. Green LED indicates Kilo-ampere (kA).</p>
	KM96-3V	<p><b>Display:</b> 3 windows.  <b>Function:</b> Display 3 Phase Voltage Simultaneously.  <b>Range:</b> AC 50-600V.</p>
	KM96-3AV	<p><b>Display:</b> 3 windows.  <b>Function:</b> Press Key "A/V" For Selecting Measuring Function: Display 3 Phase Current Simultaneously OR Display 3 Phase Voltage Simultaneously.  <b>Ranges:</b>            Direct Measurement Current: AC 0– 5A..            For Current above 5A, Current Transformer (C.T.) must be used.            Press Key "C" to select desirable C. T. Ratio.            The following are the available C.T. Ratios:            10A/5A, 15A/5A, 20A/5A, 25A/5A, 30A/5A, 40A/5A, 50A/5A,60A/5A, 70A/5A, 75A/5A, 80A/5A, 100A/5A, 120A/5A, 150A/5A, 160A/5A,200A/5A, 250A/5A, 300A/5A, 400A/5A, 500A/5A, 600A/5A, 700A/5A, 750A/5A, 800A/5A, 1kA/5A, 1.2kA/5A,1.5kA/5A, 1.6kA/5A, 2kA/5A, 2.5kA/5A, 3kA/5A, 4kA/5A, 5kA/5A,6kA/5A, 7kA/5A,7.5kA/5A, 8kA/5A.            Note: Red LED indicates Ampere. Green LED indicates Kilo-ampere (kA).            Voltage: AC 50-600V.</p>
STANDARD FEATURES		 <ul style="list-style-type: none"> <li>• This key is for selecting C.T. ratio.</li> <li>• This Key for setting measuring function. (AV)</li> </ul>
DIMENSION		